



Product: 0980 LSL 3311-121-0006-008 ☑

# LioN-Xlight 8xIO-Link Class A with ModbusTCP

#### **Product Description**

LioN-X IO-Link Master, Single Protocol Modbus TCP, IoT Protocol REST, 8 IO-Link Master Ports Class A, metal housing IP67, IP69K, 60mm, 8 x M12 A-coded I/O connection 5-poles, 2 x M12 D-coded Ethernet connection 4-poles, 2 x M12 L-coded power supply

#### **Technical Specifications**

## **Product Description**

Brand:	Belden
Product Family:	I/O Systems: Active - Standalone
Product Sub Family:	LioN-Xlight
Item Description:	0980 LSL 3311-121-0006-008
Part Number:	935701004

#### **Product Life Cycle**

Device Type:	IO-Link Master
Protocol:	Modbus TCP
I/O Function:	8 IOL (Class A)
Bus Connection:	M12, 4-poles, D-coded
Power Connection (System Supply):	M12 Power, 5-poles, L-coded
I/O Connection:	M12, 5-poles, A-coded
I/O Type:	IO-Link Master

#### **General Data**

Housing Material:	Metal, zinc die-cast
Housing Plating:	Nickel, matt
Housing Color:	Grey Metallic
Protection Degree / IP Rating**:	IP65, IP67, IP69K
Potted:	Yes
Dimensions (W x H x D):	60 mm x 31 mm x 200 mm
Weight:	500 g
Ambient Temperature (Operation)*:	-20 °C to 60 °C
Ambient Temperature (Storage/Transport):	-20 °C to 60 °C
Permissible Humidity (Operation):	5 % 95 % (For UL applications max. 80 %)
Permissible Humidity (Storage/Transport):	5 % 95 % (For UL applications max. 80 %)
Air Pressure (Operation):	80 kPa 106 kPa (up to 2000 m above sea level)
Air Pressure (Storage/Transport):	80 kPa 106 kPa (up to 2000 m above sea level)
Flammabilty Class:	UL 94 (IEC 61010)
Protection Class:	III, IEC 61140, EN 61140, VDE 0140-1
Pollution Degree:	3 acc. to EN 60664-1, VDE 0110-1
Vibration Resistance:	15 g / 5 -500 Hz
Shock Resistance:	50 g / 11ms
Contact Base Material:	M12, D-coded, CuSn, Gold-plated   M12 Power, L-coded, CuNi, Gold-plated

Contact Bearer Material:	PA / TPU
O-Ring Material:	FKM
Mounting:	$2\ hole\ screw\ mounting.\ Use\ standard\ M4\ x\ 25\ /\ 30\ screws\ with\ toothed\ lock\ washer\ (as\ per\ DIN\ 125)\ and\ self-locking\ nuts.$
Fastening Torque (Fixing Screw):	M4: 1 Nm
Fastening Torque (Ground Connection (FE)):	M4: 1 Nm
Fastening Torque (Bus Connection):	M12: 0.5 Nm
Fastening Torque (Power Connection):	M12: 0.5 Nm
Fastening Torque (I/O Connection):	M12: 0.5 Nm
Accessories to Order Separately:	Ethernet cable, mounting adapter, sensor/actuator cable, power cable

#### **Modbus TCP**

Protocol:	Modbus TCP
Connection:	M12, 4-poles, D-coded
Number of Connections:	2
Device Type:	Modbus Slave
Specification:	Modbus application protocol V1.1b

## **IIoT Protocols**

	REST API:	Cyclic data read/write, Diagnosis data, Event data	
--	-----------	--	--

## **Power Supply**

Connection Module Supply Voltage:	M12 Power, 5-poles, L-coded
Number of Connections:	2
Module Supply Voltage (Nominal):	24 V DC (SELV/PELV)
Module Supply Voltage (Range):	20V DC to 30 V DC
Reverse Polarity Protection:	Yes
Status Indicator (System Supply):	LED green
Diagnostic Indicator:	LED red
Connection Sensor Supply Voltage:	M12 Power, 5-poles, L-coded
Sensor Supply Voltage (Nominal):	24 V DC (SELV/PELV)
Sensor Supply Voltage (Range):	20V DC to 30 V DC
Reverse Polarity Protection:	Yes
Status Indicator (Sensor Supply):	LED green
Diagnostic Indicator:	LED red

## **IO-Link Master Channels**

Number of IO-Link Master Channels:	max. 8, configurable
Connection:	M12, 5-poles, A-coded
IO-Link Class A Ports:	8x, X1 to X8
IO-Link Specification:	V1.1.3
Parameter Storage:	Supported
Supported COM Modes:	4.8 kBaud (COM 1), 38.4 kBaud (COM 2), 230.4 kBaud (COM 3)
Cycle Time / Update Rate:	min. 1 ms for all channels at 32 Byte IN / OUT
Nominal Voltage:	24 V DC via US (system power supply)
Nominal Current C/Q (Pin 4):	500mA
Nominal Current 1L+ (Pin 1):	2A
Perm. Conductor Length to Device:	≤ 20 m
Status Indicator (IOL):	LED green per channel
Diagnostic Indicator:	LED red per port

## **Digital Input Channels**

Number of Digital Input Channels:	up to 16
Connection:	M12, 5-poles, A-coded
Number of Ports:	8x, X1 to X8
Channel Type:	Type 1 acc. to IEC 61131-2
Input Wiring:	2-, 3-, 4-wire
Nominal Voltage:	24 V DC via US (module power supply)

Nominal Current:	typ. 5 mA
Sensor Current Supply:	max. 4A per port via Pin1L+
Sensor Type:	PNP
Input Voltage Range "0" signal:	-3 V DC+5 V DC
Input Voltage Range "1" signal:	15 V DC 30 V DC
Input Filter Time:	configurable
Protective Circuit:	Electronicaly: Overload protection, short-circuit protection
Status Indicator (Inputs):	LED white or yellow per channel
Diagnostic Indicator:	LED red per port

## **Digital Output Channels**

Number of Digital Output Channels:	up to 8
Connection:	M12, 5-poles, A-coded
Number of Ports:	8x, X1 to X8
Channel Type:	p-switching
Output Wiring:	2-, 3-wire
Nominal Voltage:	24 V DC via US
Output Current per Channel:	max. 500mA
Galvanically Isolated:	No
Protective Circuit:	Electronicaly: Overload protection, short-circuit protection
Overload Behavior:	Auto off and on switching / Manual restart
Status Indicator (Outputs):	LED white or yellow per channel
Diagnostic Idicator:	LED red per port

## **Electrical Isolation**

US (System Supply Voltage) / FE:	500 V DC
US / UL (Actuator Supply Voltage):	500 V DC
UL / FE:	500 V DC
Uaux / FE:	500 V DC
Bus connection / FE:	2000 V DC

## **EMC Conformance**

EMC Directive:	2014/30/EU
EN 61000-4-2 Electrostatic Discharge (ESD):	Criterion B; 4 kV contact discharge, 8 kV air discharge
EN 61000-4-3 Electromagnetic Field:	Criterion A; Field intensity: 10 V/m
EN 61000-4-4 Fast Transients (Burst):	Criterion B, 2 kV
EN 61000-4-5 Surge Voltage:	Criterion B; DC supply lines: $\pm 0.5 \text{ kV/} \pm 0.5 \text{ kV}$ (symmetrical/asymmetrical); For I/O ports with cables $\leq 30 \text{m}$
EN 61000-4-6 Conducted immunity:	Criterion A; Test voltage 10 V
EN 55032 Radio Interference Properties:	Class A

# Safety & Environmental Compliance

CE:	Yes
RoHS Compliant:	Yes
China RoHS-Compliant:	Yes

## **Approvals**

UL:	cULus Listed, UL 61010-1
CSA:	Yes, via UL
IO-Link:	Yes

#### Notes

Protection Degree / IP Rating Note:	*IP Rating test performed by Belden with Belden Connectors only
System Power Supply Connection Note:	*do not connect / disconnect under voltage!

## Variants

#### © 2025 Belden, Inc

#### All Rights Reserved.

Although Belden makes every reasonable effort to ensure their accuracy at the time of this publication, information and specifications described here in are subject to error or omission and to change without notice, and the listing of such information and specifications does not ensure product availability.

Belden provides the information and specifications herein on an "ASIS" basis, with no representations or warranties, whether express, statutory or implied. In no event will Belden be liable for any damages (including consequential, indirect, incidental, special, punitive, or exemplary damages) whatsoever, even if Belden has been advised of the possibility of such damages, whether in an action under contract, negligence or any other theory, arising out of or in connection with the use, or inability to use, the information or specifications described herein.

All sales of Belden products are subject to Belden's standard terms and conditions of sale.

Belden believes this product to be in compliance with all applicable environmental programs as listed in the data sheet. The information provided is correct to the best of Belden's knowledge, information and belief at the date of its publication. This information is designed only as a general guide for the safe handling, storage, and any other operation of the product itself or the one that it becomes a part of. The Product Disclosure is not to be considered a warranty or quality specification. Regulatory information is for guidance purposes only. Product users are responsible for determining the applicability of legislation and regulations based on their individual usage of the product.