

Product: FX Brilliance OM1 LC Keyed ☑





00

Product Description

FX Brilliance Universal OM1 LC Keyed Mechanical Connector

TIA 568.3-D (MM)

Technical Specifications

Product Overview

Environmental Space:	Indoor
Suitable Applications:	Indoor termination of fiber cables: Patch panels, Communication outlets, Fiber-to-the-desk, Distribution frames, Campus, Customer premise, Access network, Data Centers

Construction

Fiber Cable Construction



Mechanical Characteristics

Mechanical Specifications

intermateability Requirement	Compliant with TIA/EIA-604-10A (FOCIS 10)
Operating Temp Range	-40°C to +75°C
Storage Temp Range	-40°C to +60°C
Durability	500 cycles, less than 0.2 dB change, FOTP-21
Maximum Insertion Loss:	0.50 dB
Typical Insertion Loss:	0.20 dB
Minimum Reflectance @ 1550	0nm: -25 dB
Termination Style:	Mechanical
Durabilities@Termination1:	500 cycles, less than 0.2 dB change, FOT

Temperature Range

Operating Temperature Range:	-40°C to +75°C
Storage Temperature Range:	-40°C to +60°C

Product Material

Materials

Description	Material	Color
Boot	Rubber	Black
Protective Ferrule Cap	Plastic	Opaque
Connector Body	Plastic	Beige
Ferrule	Ceramic	

Standards

EU Directive 2011/65/EU (RoHS 2):	Yes
MII Order #39 (China RoHS):	EUP 50
Safety Listing:	ACA

Related Part Numbers

Included Parts:	900 μm boot, dust cap
Related Parts:	FiberExpress Brilliance installation kits, Breakout kits

Variants

Item #	Color	Packaging	UPC
AX105224-B25	Aqua	25-Pack	611589105965
AX105219-B25	Black	25-Pack	611589105910
AX105221-B25	Blue	25-Pack	611589105934
AX105225-B25	Brown	25-Pack	611589105972
AX105217-B25	Green	25-Pack	611589105897
AX105220-B25	Orange	25-Pack	611589105927
AX105216-B25	Red	25-Pack	611589105880
AX105223-B25	Rose	25-Pack	611589105958
AX105226-B25	Slate	25-Pack	611589105989
AX105222-B25	Violet	25-Pack	611589105941
AX105227-B25	White	25-Pack	611589105996
AX105218-B25	Yellow	25-Pack	611589105903

Product Notes

Packaging:	Individually packaged in a sealed plastic bag. Twenty-five (25) connectors come in a dust and moisture resistant blister package.
Notes:	Refer to Installation Guide PX105234 for installation procedures. Supplied with FiberExpress Brilliance installation kit. Fiber can be reterminated up to 5 times with the same connector.

History

Update and Revision:	Revision Number: 0.53 Revision Date: 03-04-2023

© 2024 Belden, Inc

All Rights Reserved.

Although Belden makes every reasonable effort to ensure their accuracy at the time of this publication, information and specifications described here in are subject to error or omission and to change without notice, and the listing of such information and specifications does not ensure product availability.

Belden provides the information and specifications herein on an "ASIS" basis, with no representations or warranties, whether express, statutory or implied. In no event will Belden be liable for any damages (including consequential, indirect, incidental, special, punitive, or exemplary damages) whatsoever, even if Belden has been advised of the possibility of such damages, whether in an action under contract, negligence or any other theory, arising out of or in connection with the use, or inability to use, the information or specifications described herein.

All sales of Belden products are subject to Belden's standard terms and conditions of sale.

Belden believes this product to be in compliance with all applicable environmental programs as listed in the data sheet. The information provided is correct to the best of Belden's knowledge, information and belief at the date of its publication. This information is designed only as a general guide for the safe handling, storage, and any other operation of the product itself or the one that it becomes a part of. The Product Disclosure is not to be considered a warranty or quality specification. Regulatory information is for guidance purposes only. Product users are responsible for determining the applicability of legislation and regulations based on their individual usage of the product.